

## MH-8800G / US-903DC Pro

www.amthanhtoav.vn



<b>Model</b>	<b>US-903DC Pro</b>
Frequency Preparation...	PLL Synthesized Control
Carrier Frequency Range	502~960 MHz
S/N Ratio.....	> 105dB
T.H.D.....	<0.6%@1KHz
Display.....	LCD
Display Contents.....	Group/Channel, Antenna A/B, RF/AF Level Meter
Controls.....	Power On/Off, Channel Up/Down, Squelch Level, Audio Level, Lock-on
Audio Output Level.....	-12dB
AF Output Impedance.....	600Ω
Squelch.....	Pilot Tone, Noise and Mute
Operation Voltage.....	12-18 VDC, 900mA
Output Connector.....	2 Balanced XLR Sockets 1 Unbalanced Ø6.3mm Phone jack
Dimension(m/m).....	420mm (W)* 44mm (H)* 232mm (D)

<b>Model</b>	<b>Mh-8800Gi</b>
Frequency Preparation.....	PLL Synthesized Control
Carrier Frequency Range	502~960 MHz
RF Outputs.....	10mW ±10KHz ±48KHz
Stability.....	Channel, Battery Fuel Gauge, Sensitivity
Frequency Deviation.....	Power On/Off, Mode Setting, AF Level, Channel Up/Down, Lock-on Mode
LCD Display.....	—
Controls.....	<-60 dBC
Output connector.....	50~16,000 Hz
Spurious Emissions.....	UM3, AA 1.5V*2
Audio Frequency Response	
Battery.....	

### US-903DC Pro



#### UHF PLL Dual Channel Diversity Receiver

- \* Preset 4 groups each of 16 UHF channels.
- \* PLL (Phase-locked Loop) synthesized technology ensures stable RF transmission and reception.
- \* Diversity technology prevents dropouts in the RF link.
- \* Lock-on function mode.
- \* LCD indicates channel frequency, RF/AF level.
- \* Equipped with both XLR balanced and Ø6.3mm unbalanced outputs.
- \* Built-in charger: holds 4 AA batteries.



### Mh-8800Gi



#### UHF PLL Handheld Transmitter

- \* 64 Selectable channels.
- \* Phase-locked Loop (PLL) synthesized tuner.
- \* Advanced circuit design ensures stable signal transmission.
- \* Extended dynamic range and smooth frequency response.
- \* Noise mute and tone-key squelch.
- \* Interchangeable capsule module for either condenser or dynamic capsule.
- \* Internal antenna design.
- \* The "lock-on" function prevents tampering and RF interruption.

